

# RDC Charger

## User manual



**Robotina test d.o.o.**

OIC-Hrpelje 38 Hrpelje  
SI-6240 Kozina  
Slovenia



## Table of Contents

<b>1-ph current transformer</b> .....	5
<i>General description</i> .....	5
<i>Technical specifications</i> .....	6



# 1-ph current transformer

## Split core current transformer 50A



Model number:	<b>CT1-E-50</b>
Connect to:	Single phase power-sensor, CT terminals 1 -2
Mounting:	on wire
Dimensions:	41 × 24 × 27 mm

- Split core
- Safe operation
- Mini in size
- Very easy mounting
- Wide inner window

## General description

The CT1-E-50 split core current transformer is designed for fast and easy installation. The split core design permits non-contact current measurements through magnetic field induction without requiring that the primary wire be taken off line and disconnected for CT installation. This method permits a safer easy and portable current measurement. An internal precision burden resistor across the secondary winding of the CT provides a safe low voltage output and permits safe opening of the secondary circuit.

## Technical specifications

Frequency	50-60 Hz
Rated current	50 A
Accuracy	$\pm 1\%$ from 20% to 120% of rated current
Phase angle	less than 2 degrees at 50% of rated current
Insulation voltage	600 VAC
Maximum primary voltage	5000 VAC (insulated conductor)
Dielectric strength	2.5 kV/1mA/1min
Operating temperature	-15 to 60°C
Operating humidity	< 85 %
Case material	PC/UL94-V0
Bobin	PBT
Core	Permalloy
Internal structure	Epoxy
Leads	UL 1015, Twisted pair, 22 AWG